EN EVO® VISTALens® & EVO® VISTAShield® EN397, EN50365, EN166

A copy of this manual and the declaration of Conformity for the product can be found on the product page: documents.jspsafety.com/MODEL/LANGUAGE. For example: documents.jspsafety.com/EVOVISTALENS/EN.pdf. Before use, adjust your helmet suspension to the size of the user's head. The helmet must be worn with the peak facing forward. **EVO® VISTALens®**: 1. Place helmet on head with peak facing forward. 2. To alter the fit, adjust the harness at the rear of the helmet and ensure a comfortable fit is made around the crown of the head. 3. Lower eyewear using tabs at either side and tilt toward face, align gasket sits on eyewear and **EVO® VISTALens®**. 4. Tilt eyewear away from face and tilt to extract into helmet shell until it locks in place. 5. Loosen wheel ratchet and remove helmet. **EVO® VISTAShield®**: 1. Place helmet on head with peak facing forward. 2. To alter the fit, adjust the harness at the rear of the helmet and ensure a comfortable fit is made around the crown of the head. 3. Lower visor using tab at centre of lower edge. 4. Once visor fully lowered on alternate sides, ensure that toward the face to locate visor on ratchet block at top edge. 5. Adjust visor as necessary. **TO STOW EVO® VISTAShield®**: 1. Tilt visor away from face and lift to retract into helmet shell until it locks in place. 2. Loosen wheel ratchet and remove helmet. When not in use or during transportation, the PPE should be stored in a container such that it is out of direct sunlight, away from chemicals and abrasive substances, and cannot be damaged. To prevent contact with hot surfaces/objects. The conditions of storage are an important factor for the conservation of electrical and mechanical performance of insulating helmets. It is recommended that the storage condition is kept in the range 20 ± 15°C.

USE: The helmet is made to absorb the energy of an impact by partial destruction or damage to the shell or harness and even though such damage may not be readily apparent, any helmet subjected to severe impact should be replaced. This helmet has been designed to protect the wearer against electrical shocks by preventing passage of dangerous current through the body via the head. The helmet must be used with other insulating protective equipment when working on low voltage installations. The user should check that the electrical limits of the helmets correspond to the nominal voltage that is likely to be encountered during use. The attention of users is also drawn to the danger of modifying or removing any part of the helmet other than as recommended by the manufacturer. The helmet should not be modified by the user other than as instructed by the manufacturer. The helmet must be used with the harness correctly adjusted. Accessories and/or replacement parts or other items which in a situation where there is a risk that the insulating properties could be reduced. Accessories and/or replacement harness, chin straps, ear defenders, visors and helmet mounted lamps are available with fitting instructions from JSP. Do not apply paint, solvents, adhesives or self-adhesive labels, except those recommended by JSP. The maximum recommended storage life is 5 years.

INSPECTION AND CARE OF THE PPE: The PPE is a complete system consisting of shell with harness and ocular. The PPE's useful life is affected by many factors including the cold, heat, chemicals, sunlight and misuse. The PPE should be examined daily for signs of cracking, brittleness or deterioration of the shell, harness or eye protector. While the PPE is free from defects it is suitable for its intended purpose. If ocular becomes scratched or damaged to the extent that vision is impaired, it should be replaced. Replacement ocular are available from JSP. If in any doubt destroy the PPE. The user should be aware that there is potential risk of loss of protection due to ageing and/or inappropriate cleaning. The effectiveness of the helmet may be affected if the helmet is subjected to misuse or fails to meet the requirements of the helmet manufacturer. Do not use helmets in situations where there is a risk that the insulating properties could be reduced. Accessories and/or replacement harness, chin straps, ear defenders, visors and helmet mounted lamps are available with fitting instructions from JSP. Do not apply paint, solvents, adhesives or self-adhesive labels, except those recommended by JSP. The maximum recommended storage life is 5 years.

HENKILÖNSUOJAIMEN TARKASTAMINEN JA HOITO: Henkilönsuojain on kattava järjestelmä, johon kuuluu kuori, hihnat ja silmensuojain. Henkilönsuojaimen käyttöikään vaikuttavat useat eri tekijät, kuten kylmyys, kuumuus, kemikaalit, auringonvalo ja väärinkäyttö. Kypärä on suoritettava päivittäin ennen käyttöä halkeilun, hauraiden kohtien tai silmensuojaimessa mahdollisesti olevien selkeiden haikeamien, murtumien, haurastumisen tai vaurioiden varalta. Jos silmensuojaimessa ei ole mitään vikaa, se on käyttökelpoinen tarkoitukseensa. Jos silmensuojain naarmuuntuu tai silmensuojain on vahingoittava. Vaihtoinsinöijä on saatavissa JSP:ltä. Jos epäilet henkilönsuojaimen suojauskykyä, hävitä henkilönsuojain. Käyttäjän tulee olla tietoinen siitä, että suojaus voi heikentyä ajan myötä ja/tai epäasianmukaisen puhdistamisen seurauksena. Käyttöolosuhteet voivat vaikuttaa kypärän eristysominaisuuksiin vaaran. Normaalissa käytössä on suositeltavaa, että kypärä vaihdetaan 5 vuoden välein. Kypärän säilytysaika vaihtelee 10 vuotta sen mukaan, kumpi näistä ehdoista täyttyy ensin. Valmistajalla on merkitty kypärän lopun käyttöpäivämäärä ja eräs tällainen ehdoista täyttyy ensin. Lisätietoja: Jos olet epävarma siitä, onko kypärä tehokkaasti suojeleva, älä käytä sitä

CS EVO® VISTALens® & EVO® VISTAShield® EN397, EN50365, EN166

Kopie tohoto návodu a prohlášení o shodě k tomuto výrobku jsou uvedeny na straně produktu: dokumenty.jspsafety.com - VISTALens & EVO® VISTAShield® EN397, EN50365, EN166 - ZALOŽENÍ A PŘIPOJENÍ. Ke zvýšení pohodlí nošení a zajištění optimálního ochranného pole, zejména při použití s ochrannými brýlemi, nebo být upravena dle velikosti hlavy uživatele. Stisk helmy musí při nošení směřovat dopředu. **EVO® VISTALens®:** 1. Přilbu si nasaďte na hlavu a nastavte pomocí ráčny. 2. Vyjměte plastový upínací kolík z každého z vnějších otvorů pomocí pouzdra v její zadní části a ujistěte se, že přilba pohodlně sedí na temeni hlavy. 3. Stáhněte dolů ochranné brýle pomocí pouzdra v zadní části a ujistěte se, že přilba pohodlně sedí na temeni hlavy. 4. Upínací kolík zasuňte do otvorů na každé straně přilby a nastavte tak, aby se brýle pohodlně dotýkaly obličeje. **EVO® SPIRIT/ EVO® VISTALens® 1.** Nastavte pás tak, aby se řasenek nedotýkal a nebyl příliš volný. **EVO® VISTALens® 1.** Ochranné brýle vyklopte od obličeje a pohybem vzhůru je zatáhněte do skořepiny přilby až do zaklapnutí. 2. Povolte kolečko a přilbu seřiďte. **EVO® VISTAShield® 1.** Přilbu si nasaďte na hlavu se štítkem směrem dopředu. 2. V případě potřeby upravte velikost přilby pomocí popruhů v její zadní části a ujistěte se, že přilba pohodlně sedí na temeni hlavy. 3. Štít otáčejte směrem dopředu a nastavte jeho polohu pomocí velkého středního spodního **4.** Jakmile bude štít správně nadosaz na upevňovacích kolenních, posuňte jej směrem dolů a k obličeji, abyste dosáhli jeho umístění na kryty hlavě na horním okraji. 5. Upínací kolík zasuňte do horních otvorů. 6. V případě potřeby nastavte polohu štítu pomocí popruhů v jeho zadní části. 7. Štít vyklopte od obličeje a pohybem vzhůru jej zatáhněte do skořepiny přilby až do zaklapnutí. 2. Povolte kolečko a přilbu seřiďte. Pokud OOPP v nepoužívané nebo přerušené, měla by být uložena v originálním obalu, kde není vystavena světlu, chemikáliím a abrazivním částic, aby nedošlo k jejich poškození fyzickým kontaktem s tvrdými povrchy/předměty. Skladovací podmínky jsou důležitým aspektem pohodlné aktivace a mechanické izolační účinnosti přilby. Doporučuje se udržovat teplotu prostředí v rozmezí 20 °C a 15 °C.

POUŽITÍ: Přilbu je upůsobena k pohlcování nárazů částečnou deformací nebo poškozením skořepiny či popruhu. Je přesto třeba dbát na to, aby nebyla přilba vystavena nárazu, který by způsobil její úplné zničení, jelikož by tak nemusela být schopna poskytnout dostatečnou ochranu. Každá přilba by měla být vyměněna v případě, že byla vystavena nárazu, vymění. Tato přilba chrání uživatele před zasažením elektrickým proudem tím, že brání průchodu nebezpečného proudu těmi částmi přilby, které jsou v kontaktu s hlavou. Při práci na nízkonapěťových zařízeních je nutné spoléhat s přílbou používat další izolační ochranné prostředky. Uživatel by si měl uvědomit, že elektrické menší hodnoty přílby odpovídají minimálním nutné, se kterými přilba splňuje požadavky. Pokud je přilba vystavena nárazu nebo je na ní viditelné trhliny, ztráta, které s sebou nese úprava nebo demontáž jakýchkoli originální součástí této přilby, kterou nedoporučí výrobce přilby. Přilba by neměla být upravována za účelem nasazení příslušných částí, jiným způsobem, který nedoporučuje výrobce přilby. Přilba by neměla být upravována za účelem nasazení příslušných částí, jiným způsobem, který nedoporučuje výrobce