


Physics

From classic and cutting-edge apparatus and demos, to time-saving activities, durable equipment, and essential supplies for your lab - we have what you need to turn physics lessons into physics connections.



Specifications:

P3340 Multimeter

DC voltage:	400 mV – 1000 V, 5 ranges, $\pm 0.5\% \pm 2$ digits
AC voltage:	4 – 700 V, 4 ranges, $\pm 1.2\% \pm 3$ digits
DC current:	400 μ A – 10 A, 6 ranges, $\pm 1\% \pm 3$ digits
AC current:	400 μ A – 10 A, 6 ranges, $\pm 1.5\% \pm 5$ digits
Resistance:	400 Ω – 40 M Ω , 6 ranges, $\pm 1\% \pm 2$ digits
Capacity:	40 nF – 100 μ F, 5 ranges, $\pm 3\% \pm 5$ digits
Temperature:	-20 – 760°C, $\pm 3\% \pm 3$ digits
Display:	3¾ digit LCD, 39 mm, max: 3999
Operating voltage:	9 V battery
Safety classification:	CAT II 1000 V (IEC-1010-1)
Fuse:	F1: F 500 mA / 600 V F2: F 10 A / 600 V, $I_{max.} = 10$ A for 30 s
Dimensions:	approx. 92x195x38 mm ³
Weight:	approx. 200 g.